

TrackMix-WiFi-IP-Camera-Specifications		
	Model	Reolink TrackMix WiFi
Video & Audio	Image Sensor	1/3"+1/2.8"CMOS Sensor
	Video Resolution	Up to 3840 x 2160 (8.0 megapixels) at 25 frames/sec
	Lens	f=2.8mm@F=1.6, f=8mm@F=1.6
	Video Format	H.264,H.265
	Field of View	Horizontal: 104°-38° Vertical: 60°-21°
	Zoom Mode	6X hybrid zoom
	Day & Night	IR-cut filter with auto-switching
	Infrared Night Vision	Up to 30 meters (100ft) (LED: 2pcs/850nm)
	Color Night Vision	Spotlights: 2pcs/6500K/450 lumens
Power	Audio	Two-way audio
	DC Power	DC 12.0V--2A, <12W
Interface	Power	DC power port
	System	Reset button
	Ethernet	One 10M/100Mbps RJ45
	Storage	Micro SD card slot (Max. 256GB)
	Audio	Built-in microphone and speaker
Pan&Tilt	Pan &Tilt Range	Pan: 355°, Tilt: 0°~90°
	Pan Speed	2.5°-90°/s (Speed can be set)
	Tilt Speed	1.5°-60°/s (Speed can be set)
	Preset	32
	Auto Tracking	Support
Wi-Fi	Wireless Standard	IEEE 802.11a/b/g/n
	Operating Frequency	2.4GHz/5GHz
	Wireless Security	WPA-PSK/WPA2-PSK
Software Features	Frame Rate	Mainstream: 2fps - 25fps Substream: 4fps - 20fps
	Code Rate	Mainstream: 4096Kbps -8192Kbps Substream: 128Kbps -1228Kbps
	Browsers Supported	Edge, Chrome, Firefox, Safari
	OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android
	Smart Alarm	Motion detection; person detection; vehicle detection; pet detection
	Record Modes	Motion/scheduled recording (default: motion recording)
	Tracking Method	Digital Tracking; Pan/Tilt Tracking First; Digital Tracking First
	Protocols & Standards	HTTP, HTTPS, SSL, TCP/IP, UDP, UPNP, RTSP,RTMP, SMTP, NTP, DHCP, DNS, DDNS, P2P
	Maximal User Access	Supports up to 12 simultaneous video streams (10 substreams & 2 mainstreams); 20 users (1 admin account & 19 user accounts)
Working Environment	Work with	Google Assistant
	Temperature	Operating temperature: -10°C~+55°C (14°F~131°F)
	Humidity	Operating humidity: 10% ~ 90%
Size & Weight	Waterproof	IP65
	Dimension	228*147*129mm
	Weight	1.211kg
Warranty	Limited Warranty	2-year limited warranty. For support, visit <a href="https://support.reolink.com/hc/en-us/">https://support.reolink.com/hc/en-us/</a> .